



2 Channel Multi-Frequency Receiver

IL-AC-WM-HH-EU / IL-AC-WM-LT-EU/
IL-AC-WM-2C-LT / IL-AC-WM-2C-HH

Our receiver is a dual channel PLL tuneable UHF wireless system and is designed to work with microphones such as the Handheld Microphone [IL-AC-WM-HT-00] and Multi-Frequency Beltpack Microphone [IL-AC-WM-LT-00]. Use with our 6 Channel Mixer [IL-AC-MMX-00] for adjustment.

The receiver has a range of 60 metres, and is provided with either two Multi-Frequency Beltpack Microphones or two Handheld Microphones.

Physical Data

Dimensions	Height – 409mm (16.1") Width – 190mm (7.48") Depth – 44mm (1.73")
Weight	3.81kg (4.62lbs)
Construction	Various
Finish	Grey

Technical Data

Power Supply	12-18Vdc, 500mA
Carrier Frequencies	863 - 865MHz
Channels	81 tuneable UHF frequencies
Signal to Noise Ratio	>105dB
THD	<0.5% @ 1KHz
Frequency Response	50Hz - 18kHz \pm 1 dB
Image Rejection	>85dB
Connectors	DC in
	2 x XLRM
	6.3mm jack
	2 x BNC antenna
Output Impedance	2.2K Ω
Output Level	400mV (balanced), 200mV (unbalanced)

Features

- PLL tuneable with 81 UHF frequencies
- Pilot tone & mute circuit for stable signal
- Rack-mounting accessories included
- Supplied with mains adaptor and 4 x AA batteries
- Licence free operation in UK and Europe

Talk to us now:
+44 (0) 1732 223900 (UK & ROW)
+1 616 392 3400 (US & Canada)
www.contacta.co.uk

